

MOTIX

DV Charger/ Adaptor

MC-2U

Ver:B

USER MANUAL

IDX System Technology, Inc.

Service Center Location
IDX System Technology
24422 S Main St Suite #502
Carson, CA 90745
TEL: 1-310-328-2850
www.idxtek.com

Congratulations on your purchase of this product. Please read this user manual carefully.

Warning

Keep in mind the following considerations to prevent from fire or shock hazard!

- ◆ Do not attempt to open the charger, please contact local agent if have problems.
- ◆ Do not expose the charger to rain or moisture.
- ◆ Never use metal or other conductors to touch the inside of the charger.

Caution

- ◆ Only work in temperature between 0°C-40°C
- ◆ Keep the terminals clean and ensure the reliable connection.
- ◆ Do not cover the cooling vent.
- ◆ Keep the charger in a cold dry place.

Features

1. 2-channel independent power supply and control system which can charge two batteries simultaneously.
2. Support 1-channel adapting output with automatic identification; when adapting output, the 2-channel charging will be automatically stopped.

Specification

| | |
|--------------------|--|
| Model | MC-2U |
| Power input | 100~240VAC, 50/60Hz |
| Output | Charging DC 16.8V, 1.9A Adapting DC 12V, 1.9A |
| Power consumption | 60W |
| Compatible battery | SONY BP-U30/U60/U90, IDX SB-U50/98 |
| Dimension | 136×110×53mm |
| Net weight | 360g |

Usage

Charging

1. Connecting the charger with power lead reliably, the power indicator will light on.
2. Mount one or two compatible batteries onto the charging slot softly, the charger will intelligently charge (can charge two channels sequentially to 75% capacity, and then charge simultaneously to full). When charging, the LED charging indicator will start to flash and indicates the current capacity of each battery. (25%, 50%, 75% and 100%), When the battery is fully charged, all the 4 LEDs will light on, please remove the battery to use.

Adapting output

1. MC-2U has a DC socket output, can drive power-consumption equipments. Please make sure the voltage range and power consumption of the equipments are fit for the charger adapting output..
2. When adapting output, the 2-channel charging will be automatically stopped, the adapting indicator light on.

